

**Product summary:**

EoC SAT+TV+data terminal

**Brief description:**

The device is an EoC terminal to be used in connection with EMP-Centauri EoC multiswitches.

No settings are required, just connect the terminal according to the schematic diagram below. The terminal is powered by the coaxial cable coming from the multiswitch.

The NT13 terminal works in connection with any standard Ethernet devices according to 100BASE-TX and 10BASE-T standard.

Use only good quality coaxial cable of 75 ohm impedance to connect NT13 terminal with an EoC multiswitch.

**Technical data:**

Parameter	Condition	Value
Frequency range	SAT	950-2300 MHz
	TV	470-862 MHz,
Insertion loss	SAT	2 dB avg
	TV	2 dB avg
Data	RJ45 port	100 Mbit/s
	Coaxial input	100 Mbit/s
Power consumption	LAN active	50 mA / 12V
Dimensions (w,d,h)		5.4 x 6.0 x 3.2 cm
Temperature range		-25 ~ +60 °C
Weight		0.070 kg